

BRUKSANVISNING INSTRUCTION MANUAL NAMRON ZIGBEE SMART PLUG 16A

namron

220-240V~ 16A

Ⓝ IP20 CE  

Tilbakestill til Fabrikkinnstillinger

1. Hold nede innstillingsknappen i 10 sekunder.
2. Reléet vil settes til av-tilstand, og indikatoren vil blinke 3 ganger hver 2. sekund i 180 sekunder.

Legg til i et Zigbee-nettverk

1. Trykk og hold på innstillingsknappen i 10 sekunder.
2. Når paringsprosessen starter, vil reléet være i av-tilstand, og indikatoren vil blinke 3 ganger hver 2. sekund i 180 sekunder.
3. Når paringen er vellykket, vil indikatoren lyse kontinuerlig i 5 sekunder, og reléet vil gå tilbake til sin tilstand før paring.

Merk: Når enheten legges til i et zigbee nettverk så tilbakestilles enheten samtidig til fabrikkinnstillinger.

Touchlink

1. Trykk på innstillingsknappen 8 ganger.
2. Indikatoren vil blinke en gang hver 1. sekund for å indikere at Touchlink-modus er valgt.
3. Før fjernkontrollen innenfor 10 cm av den smartpluggen og sett fjernkontrollen i Touchlink-konfigurasjon.
4. Indikatoren vil lyse kontinuerlig i 5 sekunder når paringen lykkes. Tidsavbrudd på 180 sekunder.

Finn og Bind

1. Trykk kort på innstillingsknappen 9 ganger.
2. Den indikatoren vil blinke en gang hvert 2. sekund for å indikere at du har gått inn i Finn og Bind-modusen.

Tilbakestill strømmåleren

1. Trykk på innstillingsknappen to ganger, deretter trykk og hold på tredje gang.
2. Indikatoren vil blinke 5 ganger for å indikere at dataene er tilbakestilt.

Fjern overstrømsalarmen

1. Trykk på innstillingsknappen 3 ganger, deretter trykk og hold på fjerde gang i 5 sekunder.
2. Den blå indikatoren vil blinke langsomt 3 ganger for å vise at nullstillingen var vellykket.

Nettverksstatus

- Ikke lagt til et nettverk: Den blå indikatoren blinker en gang hver 2. sekund.
- Enhet frakoblet: Den blå indikatoren blinker to ganger hver 2. sekund.

SUPPORT ZIGBEE CLUSTER

- 0x0000: Basic - 0x0002: Device temperature configuration - 0x0003: Identify - 0x0004: Groups
- 0x0005: Scenes - 0x0006: On/Off - 0x0B04: Electrical Measurement - 0x0702: Simple Metering

Factory reset

1. Hold the setting button for 10s.
2. The relay will be set to off state and the indicator will flash 3 times every 2s, timeout 180s.

Add to a Zigbee Network

1. Long press the setting button for 10s
2. When the pairing starts the relay will be off state and the indicator will flash 3 times every 2s , timeout 180s.
3. When pairing succeed the indicator will be solid for 5s and the relay will resume the state before pairing.

Note: Long press the setting button will also factory reset the device and start pairing at the same time.

TouchLink

1. Short press setting button 8 times
2. The indicator will flash once every 1 second to indicate that it has been set into Touchlink mode.
3. Bring the remote within 10cm of the smart socket and set the remote into TouchLink commissioning.
4. The indicator will stay solid for 5s when pairing succeeds. Time out 180s.

Find and Bind

1. Short press the setting button 9 times.
2. The indicator will flash once every 2 seconds to show entered the Find and Bind mode successfully.

Reset the power meter

1. Short press the setting button twice and long press on the third time.
2. The indicator will flash 5times to show the data has been reset.

Clear over-current alarm

1. Short press the setting button three times, then long press in the fourth time for 5s
2. The blue indicator flashes slowly 3 times to show clear successfully.

Network status

- Not added to a network: the blue indicator flash once every 2s.
- Device offline: the blue indicator flashes twice every 2s.