

# Eva Motion Sensor

The wireless Zigbee Motion Sensor has a small form factor. Connects to any Zigbee compliant Home Automation system. Use the Motion Sensor to detect presence, control lighting or other Smart Home equipment.

## **The new standard for Motion Sensor**

The Motion Sensor is equipped with sensitivity-adjustable motion detection, lux meter and temperature sensor.

The Motion Sensor updates over the air (OTA).

## **Design customization and branding**

It has become evident that design and branding heavily affects the market of electronics. We therefore offer customization to suit your brand recognition.

Home. Connected.



**eva** Smart Home  
Made Simple.

# Specifications

<b>Power Source</b>	
Battery:	CR 123A
<b>Local Communication</b>	
Radio Protocol:	Zigbee 3.0, supports HA 2.1
Frequency:	2400-2483,5 MHz (IEEE 802.15.4)
<b>Environment</b>	
IP Class:	IP20 (Indoor use)
Operational temperature:	0 to +40 °C
Shipping/storage temperature:	-20 to +45 °C
Humidity range:	0 to 90% R.H.(non-condensing)
<b>General</b>	
Dimensions:	L:74 W:56 H:36(mm)
Bracket (supplied with unit):	Wall mounting
Upgrade method:	OTA (Over The Air)
Other:	Embedded temperature sensor
	Adjustable sensitivity levels on unit (button) or through app (requires support in app).
	Low battery warning
	LED indicator and pairing button
	Supervision enabled
	Tamper
Functionality that depends on support in your Hub/App:	Sensitivity adjustment

